

THEMIS observations of a gap in whistler mode chorus emissions inside the source region

U. Taubenschuss¹, O. Santolík^{2,3}, Y. V. Khotyaintsev¹, W. Li⁴,
A. Vaivads¹, O. LeContel⁵ and J. Bonnell⁶

¹ Swedish Institute of Space Physics, Uppsala, Sweden

² Faculty of Mathematics and Physics, Charles University, Prague, Czech Republic

³ Institute of Atmospheric Physics, Prague, Czech Republic

⁴ Department of Atmospheric and Oceanic Sciences, UCLA, Los Angeles, California, USA


⁵ Laboratoire de Physique des Plasmas, Ecole Polytechnique, Plaiseau, France

⁶ Space Sciences Laboratory, University of California, Berkeley, California, USA

THEMIS-D
2008/10/23, 06:00 – 07:00




GEOSPACE REVISITED
Rhodes, Greece
September 15 - 20, 2014



THEMIS-D
2008/10/23, 06:17 – 06:57

Magnetic Spectrum
Search Coil Magnetometer
Particle Burst (FFP)


whistler mode
chorus/rising tones



T96-Model for B_0

THD-Orbit
2008/10/23, 06:00 – 07:00
(SM coordinates)



$6.0 < L < 6.8$
 $MLAT \approx 2.5^\circ$
 $6.0 < MLT < 6.4$



THEMIS-D
2008/10/23, 05:00 – 08:00

Chorus-source in B_0 -minimum along active fieldline;
get B_0 -minimum from Tsyganenko-T96 model

Find distance of spacecraft to B_0 -minimum in T96-Model



At times of wave-burst snapshots, THD is actually crossing the B_0 -minimum
(THD below B_0 -minimum => negative distance)

Model has uncertainty of a few 100 km


Times of wave-burst snapshots

- Chorus rising tones
- Bursts crossing $0.5 f_{ce}$
- degree of polarization
 $D_p \approx 1$
- Ellipticity $\approx +1$ (RH)
- $\theta_k < 30^\circ$ (FAC);
 $\mathbf{k}$ quasi-parallel $\mathbf{B}_0$
- $\theta_s < 30^\circ$ and $\theta_s > 150^\circ$;
Poynting Vector $\mathbf{S}$
along/against
 $\mathbf{B}_0$ -direction

Themis_D (Wave-Burst, L1-calibrated)

2008/10/23/06:26 (DOY 297.27)

$\Delta f = 25.1$ Hz, $\Delta t = 0.0100$ sec






Magnetic Spectra - $\Sigma_i < B_i B_i^* >$

(sum of auto-correlations)




no gap:

$0.5 f_{c,e}$






small gap:

$0.5 f_{c,e}$



gap:


$0.5 f_{c,e}$




θ_S -Spectra (polar angle of Poynting Vector $\mathbf{S}$; FAC)

(blue ... $\mathbf{S}$ along $\mathbf{B}_0$, red ... $\mathbf{S}$ against $\mathbf{B}_0$)


no gap:



small gap:



gap:



9 wave-burst mode snapshots (~ 8 seconds each);

234 scanned rising tones; 11485 scanned points (along chorus trace)







-) $\mathbf{k}$ quasi-parallel $\mathbf{B}_0$; $\theta_k < 30^\circ$;
($\theta_k \ll \Psi_{\text{res}}$... resonance cone angle)

-) more bursts in upper band

-) B -Amplitude stronger in lower band; peaks at a few $100 \text{ pT Hz}^{-1/2}$

-) Lower Planarity F at $0.4 < f/f_{c,e} < 0.5$

-) Superposition of many waves with different $\mathbf{k}$ -directions



-) 2 groups of chorus:
 $\theta_s < 30^\circ$ vs. $\theta_s > 150^\circ$
(along/against $\mathbf{B}_0$ -direction)


-) Poynting Flux S stronger in lower band
-) S stronger for more field-aligned propagation

-) Lower Planarity around $\theta_s \sim 90^\circ$

9 wave-burst mode snapshots (~ 8 seconds each);

234 scanned rising tones; 11485 scanned points (along chorus trace)


Wave-bursts 1,2,3
06:23 – 06:31



-) 2 groups of chorus:
 $\theta_s < 30^\circ$ vs. $\theta_s > 150^\circ$
(along/against $\mathbf{B}_0$ -direction)

-) both groups crossing $0.5 f_{c,e}$


Wave-bursts 4,5,6
06:36 – 06:45



-) 2 groups of chorus:
 $\theta_s < 30^\circ$ vs. $\theta_s > 150^\circ$
(along/against $\mathbf{B}_0$ -direction)

-) $\theta_s > 150^\circ$: still a few bursts crossing $0.5 f_{c,e}$
 $\theta_s < 30^\circ$: small gap at $0.45 < f/f_{c,e} < 0.50$

Wave-bursts 7,8,9
06:50 – 07:20



-) 2 groups of chorus:
 $\theta_s < 30^\circ$ vs. $\theta_s > 150^\circ$
(along/against $\mathbf{B}_0$ -direction)

-) gap at $0.5 f_{c,e}$ for both groups

-) Dominant direction $\Rightarrow \theta_s > 150^\circ$
(THD left the source region?)

THEMIS-D , ESA
2008/10/23,
05:00 – 08:00

N_{tot} ... total electron density
(from S/C-potential)

smooth along trajectory
(after plasmapause crossing)

Injection of hot electrons at 06:20
--> anisotropy of keV electrons

E_{min} ... minimum resonant energy for
electrons (function of B_0 , N_{tot} , f/f_{ce})

Integration of N above E_{min} yields N_{hot}


Chorus rising tones need nonlinear
generation mechanism

Effective nonlinear wave growth for


$$0.013 < N_{hot}/N_{tot} < 0.3$$

--> fulfilled after 06:23 (1st wave-burst
snapshot)

Times of wave-burst snapshots



THD, ESA-Electrons (Reduced Mode)
2008/10/23 (DOY 297.21 - 297.33)



E_{min} for $f/f_{ce} = 0.5$

Plasmapause crossing

Conclusions

THEMIS-D is crossing the source region of whistler mode chorus rising tones on 10/23/2008.

Comparison with the Tsyganenko-T96 magnetic field model: THD is flying through the B_0 -minimum along consecutive fieldlines

Injection of hot electrons at energies > 10 keV


$0.013 < N_{hot}/N_{tot} < 0.3$ ---> effective nonlinear wave growth (electron cyclotron resonance)

N_{tot} , $\mathbf{B}_0$ show no strong gradients along THD-trajectory

06:23 – 06:30: no gap at $0.5 f_{c,e}$, opposite Poynting fluxes
--> source region extends at least 1537 km into direction perp. to B_0

06:36 – 06:44: gap at $0.5 f_{c,e}$, but still opposite Poynting fluxes
--> nonlinear damping in source region (for oblique $\mathbf{k}$)

THD, ESA-Electrons (Reduced Mode)
2008/10/23 (DOY 297.21 - 297.33)




THEMIS-D
2008/10/23,
06:15 – 06:54

smooth variations in magnetic field



smooth variations in electron density

no strong gradients – only microfluctuations



B-measured vs. B-model

Best fit between observation & model



black graph:
 B_{THD} -measured minus B_{min} -model
 gets close to 0 nT during source crossing
 => T96-model works well

blue graph:
 B_{THD} -model $\approx$ B_{min} -model for > 1h
 => THD is "grazing" the source